

ST-850 / 855 PR

Phase Sequence Indicators



ST-850



855 PR

FEATURES

- Two functions in one unit. It is designed to check phase sequence. Lamps provide on the unit will tell you whether phase is open or which phase is open at a glance.
- Large size alligator clips.
- Highly reliable. Allow you to check a wide range of 3-phase power source from 90V to 600V. Sealed against dust, the unit ensures highly dependable and trouble free performance.
- Functional design. Small lightweight and portable. Designed for maximum ease of operation.
- Safety design. No exposed metal parts. Safety features are incorporated throughout including the pushbutton switch designed to minimize damage due to negligence.

SPECIFICATIONS

| Model | ST-850 | 855 PR |
|----------------------------------|--|--|
| Voltage | 90V-600V AC | 200V-600V AC |
| Frequency Response | 50/60Hz | 50/60Hz |
| Storage Temperature & Humidity | -20°C ~ +60°C at 90% max. relative humidity | -20°C ~ +60°C at 90% max. relative humidity |
| Operating Temperature & Humidity | -10°C ~ +40°C at 80% max. relative humidity | -10°C ~ +40°C at 80% max. relative humidity |
| Dimensions | Approx. 510g | Approx. 530g |
| Cord | 1.1m each of red (R), white (S) and black (T) cord | 1.1m each of red (R), white (S) and black (T) cord |
| Accessories | Instruction manual Vinyl case | Instruction manual Vinyl case |
| Safety Standard | IEC 1010 CAT. II | IEC 1010 CAT. II |

[Top](#) / [Back to Lookup](#) / [Home](#)